	No	sensing / control	bandwidth	bits	Chassis #	ADC/DAC #	Comments	Variable (Beckhoff)	Variable (EPICS)
A1.1 PSL-EPICS control									
A1.2 pre modeclean PMC									
DB9 Connector 1 (0x1)									
out1	1			1	2	DAC_2_0			
enable	1		NA	1	2	DAC_2_1	enables automation of TE/ET2 input		(tbd)PSL-PMC_TF_IN_ON
Enable locking (lock on)	1		NA	1	2	DAC_2_2	turns lock acquisition on		(tbd)PSL-PMC_LOCK_ON
Ramp on/off (ramp on)	1		NA	1	2	DAC_2_3	turns ramp on		(tbd)PSL-PMC_RAMP_ON
DB9 Connector 2 (0x3)									
Set gain	1		NA	16	2	DAC_2_8	set gain of control loop		(tbd)PSL-PMC_GAIN
Set power threshold (ref)	NA		NA	16	2	DAC_2_9	sets threshold, which the acquisition automation assumes PMC is locked		(tbd)PSL-PMC_REFPWT
Set error point offset (in offset)	1		NA	16	2	DAC_2_10	sets error point offset in offset-lock control loop		(tbd)PSL-PMC_ERRPOINT
heater			NA		2	DAC_2_11	set offset of heater and hence operation point of PMC temp. loop		(tbd)PSL-PMC_HEATER
DB9 Connector 3 (0x2)									
gain lock	1		NA	16	2	DAC_2_4	opens feedback loop		(tbd)PSL-PMC_BLSWEING
gain boost	1		NA	16	2	DAC_2_5	activates integrator o control loop		(tbd)PSL-PMC_BOOST
calibration line in (TIN)	1		NA	16	2	DAC_2_6	summation point for calibration lines, used for alignment carry		(tbd)PSL-PMC_TF_IN
ramp			NA		2	DAC_2_7	out ramp (would be ramp input to user digital lock acquisition is used)		(tbd)PSL-PMC_RAMP
Lasve 60									
Set power monitor	1			16	2				
Lasve 60 (gasfire)									
Relock counter	1			1	2				
DB9 Connector 4 (0x4 3)									
HV monitor	1			1	2	ADC_2_0	monitor of HV signal send to PZT actuator of PMC		(tbd)PSL-PMC_HV_MON
Mixer out monitor	1			1	2	ADC_2_1	mixer output monitor		(tbd)PSL-PMC_MIXER
Local oscillator power (LODET)	1			1	2	ADC_2_2	power of local oscillator used in demodulation electronics		(tbd)PSL-PMC_LO_POWER_MON
"resonant" trigger (TRIGGER)	1			1	2	ADC_2_7	DC signal of locking diode, used by autolock to determine if PMC is resonant		(tbd)PSL-PMC_TRIGGER
DB9 Connector 5 (0x5)									
TF B	1			16	2	ADC_2_3	test point for transfer function measurement		(tbd)PSL-PMC_TF_B
Temp	1			16	2	ADC_2_8	temperature sensor on PMC		(tbd)PSL-PMC_TEMP
TF A	1			16	2	ADC_2_9	test point for transfer function measurement		(tbd)PSL-PMC_TF_A
Resonant	1				2	ADC_2_5	binary signals, 1 if auto lock thinks PMC is resonant		(tbd)PSL-PMC_RESONANT_MON
A1.2 Intensity stabilization ISS									
DB9 Connector 1 (0x2)									
AOM	1			16	1	ADC_3_0	ISS actuator signal send to AOM		(tbd)PSL-ISS_AOM
QPD-dif	1			16	1	ADC_3_6	quadrant photodiode dc-signal		(tbd)PSL-ISS_QPDDIX
QPD-sum	1			16	1	ADC_3_7	quadrant photodiode dc-signal		(tbd)PSL-ISS_QPDSUM
DB9 Connector 2 (0x1)									
reference out	1			16	1	DAC_3_0	reference to which the ISS stabilizes the power		(tbd)PSL-ISS_REFSIGNAL
transfer 1 in	1			16	1	DAC_3_1	summation into error point		(tbd)PSL-ISS_TRANSFER1_IN1
transfer 2 in	1			16	1	DAC_3_2	summation into outer loop signal		(tbd)PSL-ISS_TRANSFER2_IN1
set gain	1			16	1	DAC_3_3	ISS control loop gain		(tbd)PSL-ISS_GAIN
DB9 Connector 3 (0x3)									
offset out	1			16	1	DAC_3_4	offset added to control signal to enable AOM to increase power		(tbd)PSL-ISS_CTRL_OFFSET
interchange of photodiodes	1			16	1	DAC_3_5	switch if photodiode A of B is used as in loop sensor		(tbd)PSL-ISS_DIODEOP_PD_SELECT
close outer loop	1			16	1	DAC_3_6	switch to open/close second ISS feedback loop		(tbd)PSL-ISS_SECONDLOOP_CLOSED
close feedback control loop	1			16	1	DAC_3_7	switch to open/close feedback loop		(tbd)PSL-ISS_LOOP_STATE
DB9 Connector 4 (0x41)									
PD A monitor	1			16	1	ADC_3_0	monitor signal of photodiode A, (at output of signal conditioning filter)		(tbd)PSL-ISS_PDMON1A
PD B monitor	1			16	1	ADC_3_1	monitor signal of photodiode B, (at output of signal conditioning filter)		(tbd)PSL-ISS_PDMON1B
Outer PD monitor	1			16	1	ADC_3_2	monitor signal of second loop photodiode		(tbd)PSL-ISS_OUTERPDMON
reference signal out					1	ADC_3_3	low pass filtered readback of ref. signal		(tbd)PSL-ISS_REFSIGNALOUT
DB9 Connector 5 (0x42)									
transfer 1A	1			16	1	ADC_3_4	signal infront of summation point in first loop		(tbd)PSL-ISS_TRANSFER1A
transfer 1B	1			16	1	ADC_3_5	signal behind summation point in first loop		(tbd)PSL-ISS_TRANSFER1B
transfer 2A	1			16	1	ADC_3_6	signal infront of summation point in second loop		(tbd)PSL-ISS_TRANSFER2A
transfer 2B	1			16	1	ADC_3_7	signal behind summation point in second loop		(tbd)PSL-ISS_TRANSFER2B
A1.3.1 second loop stiffening									
DB9 Connector 1 (0x41)									
PD1	1			16	Rear	ADC_3_20			(tbd)PSL-ISS_SECONDLOOP_PD1
PD2	1			16	Rear	ADC_3_21			(tbd)PSL-ISS_SECONDLOOP_PD2
PD3	1			16	Rear	ADC_3_22			(tbd)PSL-ISS_SECONDLOOP_PD3
PD4	1			16	Rear	ADC_3_23			(tbd)PSL-ISS_SECONDLOOP_PD4
DB9 Connector 2 (0x42)									
PD5	1			16	Rear	ADC_3_24			(tbd)PSL-ISS_SECONDLOOP_PD5
PD6	1			16	Rear	ADC_3_25			(tbd)PSL-ISS_SECONDLOOP_PD6
PD7	1			16	Rear	ADC_3_26			(tbd)PSL-ISS_SECONDLOOP_PD7
PD8	1			16	Rear	ADC_3_27			(tbd)PSL-ISS_SECONDLOOP_PD8
A1.3.2 second loop QPD									
DB9 Connector 1 (0x41)									
SEC1	1			16	SEC	ADC_3_16	PD array QPD Segment 1		(tbd)PSL-ISS_SECONDLOOP_QPD_SEC1
SEC2	1			16	SEC	ADC_3_17	PD array QPD Segment 2		(tbd)PSL-ISS_SECONDLOOP_QPD_SEC2
SEC3	1			16	SEC	ADC_3_18	PD array QPD Segment 3		(tbd)PSL-ISS_SECONDLOOP_QPD_SEC3
SEC4	1			16	SEC	ADC_3_19	PD array QPD Segment 4		(tbd)PSL-ISS_SECONDLOOP_QPD_SEC4
A1.3.3 second loop servo									
DB9 Connector 1 (0x41)									
PD 5-8 SUM	1			16	2	ADC_3_10	sum of PDs 5-8		(tbd)PSL-ISS_SECONDLOOP_PD_56_SUM
ref signal out	1			16	2	ADC_3_11	reference voltage readback		(tbd)PSL-ISS_SECONDLOOP_REFSIGNAL_MON
spare	1			16	2	ADC_3_12			
PD 1-4 SUM				16	2	ADC_3_13	sum of PDs 1-4		(tbd)PSL-ISS_SECONDLOOP_PD_14_SUM
DB9 Connector 2 (0x1)									
ref voltage	1			16	2	DAC_3_8	reference voltage		(tbd)PSL-ISS_SECONDLOOP_REF_SIGNAL
PD SWITCH	1			16	2	DAC_3_9	in loop PD switch		(tbd)PSL-ISS_SECONDLOOP_PD_SW
servo on/off	1			16	2	DAC_3_10	servo on/off		(tbd)PSL-ISS_SECONDLOOP_SERVO_ON
gain	1			16	2	DAC_3_11	variable gain		(tbd)PSL-ISS_SECONDLOOP_GAIN
DB9 Connector 3 (0x2)									
boost on/off	1			16	2	DAC_3_12	boost on/off		(tbd)PSL-ISS_SECONDLOOP_BOOST_ON
integrator	1			16	2	DAC_3_13	integrator on/off		(tbd)PSL-ISS_SECONDLOOP_INT_ON
spare	1			16	2	DAC_3_14			
spare	1			16	2	DAC_3_15			
A1.3 frequency stabilization FIS									
TFFSB Beckhoff									
DB9 Connector (0x41)									
PLL					1	ADC_1_0	FSS loop enclosure		(tbd)PSL-FIS_SNSER
INT					1	ADC_1_1	LEMO input INT at TTFSB fieldbox		(tbd)PSL-FIS_INT
FastM_OUT				16	1	ADC_1_2	monitor of NPRO PZT signal		(tbd)PSL-FIS_FAST_MON
PCM_OUT				12	1	ADC_1_3	monitor of signal to phase correcting pockels cell		(tbd)PSL-FIS_PC_MON
DB9 Connector (0x42)									
LSMOUT				12	1	ADC_1_4	strength of local oscillator signal		(tbd)PSL-FIS_LO_POWER_MON
LSLOCK					1	ADC_1_5	LEMO output LSLOCK at TTFSB fieldbox		(tbd)PSL-FIS_LSLOCK_MON
REFPDC				16	1	ADC_1_6	DC signal of photodiode in reflection of reference cavity		(tbd)PSL-FIS_RPTD_DC
TPD				16	1	ADC_1_7	DC signal of photodiode in transmission of reference cavity		(tbd)PSL-FIS_TPD_DC
DB9 Connector (0x41)									
CSI				16	2	DAC_1_0	common gain		(tbd)PSL-FIS_COMMON_GAIN
FSI				16	2	DAC_1_1	signal gain for combined inte error point		(tbd)PSL-FIS_INTEGRATOR_GAIN
PSI				16	2	DAC_1_2	fast pzt gain (NPRO PZT)		(tbd)PSL-FIS_FAST_GAIN
SLOW					2	DAC_1_3	signal given to the SLOW BNC output of TTFSB (connected to RAMP IN)		(tbd)PSL-FIS_FAST_RAMP_INJECTION
DB9 Connector (0x2)									
TST IN					2	DAC_1_4	enables BNC TEST1 IN (summation at output of MIXER (all input of LP filter)		(tbd)PSL-FIS_TEST1_ON
TST2					2	DAC_1_5	enables output of LP filter (after error point and before all output of MIXER, LP filter)		(tbd)PSL-FIS_TEST2_ON
RSFB					2	DAC_1_6	enable/disable control loop after error point and effect of ramp injection in last gain		(tbd)PSL-FIS_LOOP_CLOSED
TEMP					1	ADC_1_7	signal to LEMO TEMP at TTFSB PIB		(tbd)PSL-FIS_NPRO_TEMP
VCO Beckhoff	VCO at the sites communicates via Beckhoff								
DB9 Connector (0x41)									
VCO_OPWR					1	ADC_1_8	VCO power monitor		(tbd)PSL-FIS_VCO_POWER_MON
					1	ADC_1_9			
					1	ADC_1_10			
					1	ADC_1_11			
DB9 Connector (0x2)									
MODLEVEL					2	DAC_1_10	sets the level of the rf signal send from the VCO to the FISS AOM		(tbd)PSL-FIS_VCO_MODLEVEL
TEST_EN					1	DAC_1_11	enables the TEST input (BNC at VCO box)		(tbd)PSL-FIS_VCO_TEST_ON
WIDE_DIV					1	DAC_1_12	enables the WIDE input (BNC at VCO box, wideband actuator signal from MC loop)		(tbd)PSL-FIS_WIDE_ON
A1.4 diagnostic breadboard DBB									
DB25 Connector 1									
QPD1-QA	1				2	ADC_2_0	quadrant photodiode 1 dc -DC		(tbd)PSL-DBB_QPD1_QA
QPD1-QB	1				2	ADC_2_1	quadrant photodiode 1 dc -DC		(tbd)PSL-DBB_QPD1_QB
QPD1-QC	1				2	ADC_2_2	quadrant photodiode 1 sum -DC		(tbd)PSL-DBB_QPD1_QC
QPD1-QD	1				2	ADC_2_3	quadrant photodiode 1 sum -DC		(tbd)PSL-DBB_QPD1_QD
QPD2-QA	1				2	ADC_2_4	quadrant photodiode 1 dc -DC		(tbd)PSL-DBB_QPD2_QA
QPD2-QB	1				2	ADC_2_5	quadrant photodiode 1 sum -DC		(tbd)PSL-DBB_QPD2_QB
QPD2-QC	1				2	ADC_2_6	quadrant photodiode 1 sum -DC		(tbd)PSL-DBB_QPD2_QC
TPD-QDB	1				2	ADC_2_7	photodiode in transmission of cavity (not amplified)		(tbd)PSL-DBB_TPD_QDB
DB25 Connector 2									
QPD1-DA	1				2	ADC_2_8	quadrant photodiode 1 dc - demodulated		(tbd)PSL-DBB_QPD1_DA
QPD1-DY	1				2	ADC_2_9	quadrant photodiode 1 dc - demodulated		(tbd)PSL-DBB_QPD1_DY
QPD2-DA	1				2	ADC_2_10	quadrant photodiode 1 dc - demodulated		(tbd)PSL-DBB_QPD2_DA
QPD2-DY	1				2	ADC_2_11	quadrant photodiode 1 dc - demodulated		(tbd)PSL-DBB_QPD2_DY
PDMON	1				2	ADC_2_12	photodiode in front of cavity with signal conditioning		(tbd)PSL-DBB_PDMON
HOMON	1				2	ADC_2_13	actuator signal of locking loop		(tbd)PSL-DBB_HOMON
RPD_AC	1				2	ADC_2_14	power noise sensing photodiode AC		(tbd)PSL-DBB_RPD_AC
DB25 Connector 3									
TPD-ddB/B	1				2	ADC_2_15	photodiode in transmission of cavity (dbdB gain output)		(tbd)PSL-DBB_TPD_dbdB
TPD-ddB/A	1				2	ADC_2_16	photodiode in transmission of cavity (dbdB gain output)		(tbd)PSL-DBB_TPD_dbdB
SHUTTER-IRIG	1				2	ADC_2_17	noise shutter required		(tbd)PSL-DBB_SHUTTER_IRIG
AUX-INPUT1	1				2	ADC_2_18			(tbd)PSL-DBB_AUX_INPUT1
AUX-INPUT2	1				2	ADC_2_19			(tbd)PSL-DBB_AUX_INPUT2
AUX-INPUT3	1				2	ADC_2_20			(tbd)PSL-DBB_AUX_INPUT3
AUX-INPUT4	1				2	ADC_2_21			(tbd)PSL-DBB_AUX_INPUT4
RMT-RESEACK	1				2	ADC_2_22			(tbd)PSL-DBB_RMT_RESEAK
DB25 Connector 4									
CTRLY1	1				2	DAC_2_0	control signal length control		(tbd)PSL-DBB_CTRLY1
CTRLX1	1				2	DAC_2_1	control signal alignment control		(tbd)PSL-DBB_CTRLX1
CTRLY2	1				2	DAC_2_2	control signal alignment control		(tbd)PSL-DBB_CTRLY2
CTRLX2	1				2	DAC_2_3	control signal alignment control		(tbd)PSL-DBB_CTRLX2
CTRLY3	1				2	DAC_2_4	control signal alignment control		(tbd)PSL-DBB_CTRLY3
PHASE	1				2	DAC_2_5			(tbd)PSL-DBB_PHASE
LENS1	1				2	DAC_2_6	actuatie mode matching lens 1		(tbd)PSL-DBB_LENS1
LENS2	1				2	DAC_2_7	actuatie mode matching lens 2		(tbd)PSL-DBB_LENS2
DB25 Connector 5									
LENS-LATCH	1				2	DAC_2_8			(tbd)PSL-DBB_LENS-LATCH
TRANS_DBB	1				2	DAC_2_9			(tbd)PSL-DBB_TRANS_DBB
RMT	1				2	DAC_2_10			(tbd)PSL-DBB_RMT
MODEOFF	1				2	DAC_2_11			(tbd)PSL-DBB_MODEOFF
SCANNODE	1				2	DAC_2_12			(tbd)PSL-DBB_SCANNODE
SHUTTER-MULTIPLEX	1				2	DAC_2_13			(tbd)PSL-DBB_SHUTTER_MULTIPLEX
FILTER-SWITCH1	1				2	DAC_2_14			(tbd)PSL-DBB_FILTER_SWITCH1
FILTER-SWITCH2	1				2	DAC_2_15			(tbd)PSL-DBB_FILTER_SWITCH2

To AA Ch. 1-8

Pins	Name	AD ch.
1-14	QPD1-QA	0
2-14	QPD1-QB	1
3-14	QPD1-QC	2
4-14	QPD1-QD	3
5-14	QPD2-QA	4
6-14	QPD2-QB	5
7-20	RPD-QC	6
8-21	TPD-DDB	7

To AA Ch. 9-16

Pins	Name	AD ch.
1-14	QPD1-DX	8
2-14	QPD1-DY	9
3-14	QPD-DX	10
4-14	QPD2-DY	11
5-14	QPD2-DX	12
6-19	ISCTRCR	13
7-20	HOMON	14
8-21	RPAC	15

To AA Ch. 17-24

Pins	Name	AD ch.
1-14	TPD-ddDB	16
2-14	TPD-ddDB	17
3-14	SHUTTER-IRIG	18
4-14	AUX-INPUT1	19
5-14	AUX-INPUT2	20
6-19	AUX-INPUT3	21
7-20	AUX-INPUT4	22
8-21	RMT-READBACK	23

To AO Ch. 1-8

Pins	Name	DA ch.
2-19	CTRLZ	0
2-19	CTRLUX	1
3-16	CTRLUY	2
4-17	CTRLZX	3
5-18	CTRLZY	4
6-19	PHASE	5
7-20	LENS1	6
8-21	LENS2	7

To AO Ch. 9-16

Pins	Name	DA ch.
1-14	LENS-LATCH	8
2-14	SHUTTER-DBB	9
3-16	RMT	10
4-17	MODEOFF	11
5-18	SCANNODE	12
6-19	SHUTTER-MULTIPLEX	13
7-20	FILTER-SWITCH1	14
8-21	FILTER-SWITCH2	15

A1.5 injection locking UL (EPICS part)

injection locking is analog loop, lock acquisition is guided by Beckhoff (see A2.3), EPICS used for fast sensing and signal injection (via PMC RT-mode)

DB9 Connector 4 (0x2)

HV monitor	1			1	2	ADC_2_10	monitor of HV signal send to PZT actuator of ULS		(tbd)PSL-ULS_HV_MON
Mixer out monitor	1			1	2	ADC_2_11	error signal of injection locking control loop		(tbd)PSL-ULS_MIXER
Local oscillator power (LODET)	1			1	2	ADC_2_12	power of local oscillator used in demodulation electronics		(tbd)PSL-ULS_LO_POWER_MON
"resonant" trigger (TRIGGER)	1			1	2	ADC_2_17	DC signal of locking diode, used by autolock to determine if ULS is resonant		(tbd)PSL-ULS_TRIGGER
DB9 Connector 5 (0x41)									
TF B	1			16	2	ADC_2_13	test point for transfer function measurement		(tbd)PSL-ULS_TF_B
Temp					2	ADC_2_18	temperature sensor on PMC		
TF A					2	ADC_2_19	test point for transfer function measurement		(tbd)PSL-ULS_TF_A
Resonant					2	ADC_2_15	binary signals, 1 if auto lock thinks PMC is resonant		(tbd)PSL-ULS_RESONANT_ON

A1.6 PSL monitoring Field Box module for HPL photodiodes, RT transfer/function measurements and channels viewed in design

DB9 Connector 1

OSC photodiode - amplifier power in	1			16	2	ADC_3_0	monitoring photodiode in HPL - signal from front-end at output of Faraday Isolator		(tbd)PSL-OSC_PDAMP_DC
OSC photodiode - reverse power (R) reflected	1			16	2	ADC_3_1	monitoring photodiode in HPL - power in reverse direction, split of AP1		(tbd)PSL-OSC_PDSIG_DC
OSC photodiode - reverse power (T) reflected	1			16	2	ADC_3_2	monitoring photodiode in HPL - power in reverse direction, split of AP1		(tbd)PSL-OSC_PDSIG_AC
OSC photodiode - oscillator internal power	1			16	2	ADC_3_3	monitoring photodiode in HPL - circulating light power in HPL oscillator		(tbd)PSL-OSC_PDINT_DC

DB9 Connector 2

OSC photodiode - amplifier power in -AC	1			16	2	ADC_3_4	monitoring photodiode in HPL - signal from front-end at output of Faraday Isolator		(tbd)PSL-OSC_PDAMP_AC
OSC photodiode - reverse power (R) reflected	1			16	2	ADC_3_5	monitoring photodiode in HPL - power in reverse direction, split of AP1		(tbd)PSL-OSC_PDSIG_DC
OSC photodiode - reverse power (T) reflected	1			16	2	ADC_3_6	monitoring photodiode in HPL - power in reverse direction, split of AP1		(tbd)PSL-OSC_PDSIG_AC
OSC photodiode - oscillator internal power -AC	1			16	2	ADC_3_7	monitoring photodiode in HPL - circulating light power in HPL oscillator		(tbd)PSL-OSC_PDINT_AC

DB9 Connector 3

PMC - reflected pol power meter	1			16	2	ADC_3_8	power in reflection of PMC (power meter used for installation and maintenance)		(tbd)PSL-PMC_REFL
PMC - transmitted pol power meter (installati	1			16	2	ADC_3_9	power in transmission of PMC (power meter used for installation and maintenance)		(tbd)PSL-PMC_TRANS
HPL power monitoring diode - DC	1			16	2	ADC_3_10	monitor photodiode (PD001) of output of HPL, main HPL power monitor		(tbd)PSL-PWR_HPL_DC
HPL power monitoring diode - AC	1			16	2	ADC_3_11	monitor photodiode (PD001) of output of HPL, main HPL power monitor		(tbd)PSL-PWR_HPL_AC

(tbd)PSL-PWR_PMC_SUM transmitted plus reflected power

DB9 Connector 4

water flow sensor for power meters and beams	1			16	2	ADC_3_12	used to detect too low water flow through beam dumps and power meters		(tbd)PSL-WS_FLOW
NPRO RRO monitoring PD - DC	1			16	2	ADC_3_13	monitor photodiode at input of 3W amplifier: senses NPRO power		(tbd)PSL-PWR_NPRO
NPRO RRO monitoring PD - RRO detect	1			16	2	ADC_3_14	binary signal for NPRO rf- power (in band around relaxation oscillation frequency)		(tbd)PSL-WS_NPRO_RRO
spare	1			16	2	ADC_3_15			(tbd)PSL-WS_SPARE

A1.7 PSL Input/output Field Box module for auxiliary inputs and outputs

DB9 Connector 1 (0x41)

ADC1	1			16	2	ADC_1_12			
ADC2	1			16	2	ADC_1_13			
ADC3	1			16	2	ADC_1_14			
ADC4	1			16	2	ADC_1_15			

DB9 Connector 2 (0x42)

ADC5	1			16	2	ADC_1_16			
ADC6	1			16	2	ADC_1_17			
ADC7	1			16	2	ADC_1_18			
ADC8	1			16	2	ADC_1_19			

DB9 Connector 3 (0x1)

DAC1	1			16	2	DAC_1_16			
DAC2	1			16	2	DAC_1_17			
DAC3	1			16	2	DAC_1_18			
DAC4	1			16	2	DAC_1_19			

DB9 Connector 4 (0x2)

DAC5	1			16	2	DAC_1_20			
DAC6	1			16	2	DAC_1_21			
DAC7	1			16	2	DAC_1_22			
DAC8	1			16	2	DAC_1_23			

A2 - Beckhoff Interface LVEL For information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet

A2.0 NPRO Diagnostic For information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet

A2.1 Laser Diode Control For information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet

A2.2 HPL Control injection locking is analog loop, lock acquisition is guided by Beckhoff, EPICS used for fast sensing and set point injection (see A1.5)

A2.3 Injection locking (Beckhoff part)

Set gain	1	o / -24V	1		
Enable locking (lock on)	1	o / -24V	1		
Ramp on/off (ramp on)	1	o / -24V	1		high gain, only relevant for PMC locking, switches between full and reduced power mode
enable	1	o / -24V	1		enables summation of TE/ET2 input
out1					
DB9 Connector 2					
Set power threshold (ref)	1	o / -10...10V	16		
Set error point offset (in offset)	1	o / -10...10V	16		
Set gain					
Lasve 60					
Set power monitor	1	o / -10...10V	16		
Lasve 60 (gasfire)					
Relock counter	1	o / -5V		1	

A3 - Beckhoff - Diodelasers For information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet

A3.0 Laser Diode Box Front End

LD_LED 1-4	2	o / PT1000	20 Hz	12	Set Temperature LD 1-4	chnpDiodeTempSet[1-4]
T_LED 1-4	2	o / PT1000	20 Hz	16	Input Temperature LD 1-4	chnpDiodeTempAct[1-4]
I_LED 1-4	2	o / 0-10V	20 Hz	16	Input Current LD 1-4, Amp. LD 1-4	chnpDiodeCurrentAct[1-4]
CT_LED 1-4	2	o		12	Set Current LD 1-2/3-4	chnpDiodeCurrentSet[1-2]
SC_LED 1-2/3-4	2	o / PT1000		12	Input Current LD 1-2/3-4	chnpDiodeCurrentAct[1-2]
IC_LED 1-2/3-4	2	o / 0-10V	20 Hz	12	Output Current to Diode Supply LD 1-2/3-4	chnpDiodeCurrentCtrl[1-2]
I_Diode 1-2/3-4	2	o	20 Hz	16	Input Diode Current Monitor Diode 1-2/3-4	chnpDiodeCurrentMon[1-2]
IC_LED 1-2/3-4	2	o / PT1000	20 Hz	16	Input Heatsink Temp Brushed diode 1-2/3-4	chnpSinkheatTempAct[1-2]
IT_DIBrewerd-Temp	1	o	20 Hz	1	Input Diode TempGuard	bdhnpTempGuard
I_DIBrewerd	1	o	20 Hz	1	Input	bdhnpIGuard
I_DIBrewerd-out	1	o	20 Hz	1	Output	bdhnpIGuardPowerSupplies
IC_PowerSupplyFrontEnd		for information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet			

A3.1 Laser Diode Box 1

Set temp DB1_LD1-7	7	o / PT1000	100 Hz	16	Set Temperature LD 1-7	chLDiodeTempSet[1-7]
Input temp DB1_LD1-7	7	o / 0-10V	100 Hz	16	Input Temperature LD 1-7	chLDiodeTempAct[1-7]
Output TEC DB1_LD 1-7	7	o		12	Output Current to Peltier Amp. LD 1-7	chLDiodeCurrentCtrl[1-7]
set current DB1	1		100 Hz	12	Set Current LD 1-7	chLDiodeCurrentSet[1]
Input current DB1	1	o / 0-5V	100 Hz	12	Input Current LD 1-7	chLDiodeCurrentAct[1]
Output current DB1	2	o / PT1000			Output Current Sum Diode Supply LD 1-7	chLDiodeCurrentCtrl[1]
Act temp heatsink DB1_1-2	for information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet					

A3.2 Laser Diode Box 2

Set temp_DB2_LD1-7	7	o / PT1000	100 Hz	16	Set Temperature LD 8-14	chLDiodeTempSet[1-7]
Input temp DB2_LD1-7	7	o / 0-10V	100 Hz	12	Input Temperature LD 8-14	chLDiodeTempAct[1-7]
Output TEC DB2_LD 8-14	7	o		12	Output Current to Peltier Amp. LD 8-14	chLDiodeCurrentCtrl[1-7]
set current DB2	1		100 Hz	12	Set Current LD 8-14	chLDiodeCurrentSet[2]
Input current DB2	1	o / 0-5V	100 Hz	12	Input Current LD 8-14	chLDiodeCurrentAct[2]
Output current DB2	2	o / PT1000			Output Current to Diode Supply LD 8-14	chLDiodeCurrentCtrl[2]
Act temp heatsink DB2_1-2	for information on assigned channels available in EPICS see interface D1.1 in "Digital (2)" spreadsheet					

A3.3 Laser Diode Box 3

Set temp_DB3_LD1-7	7	o / PT1000	100 Hz	16	Set Temperature LD