

# TMTS (LEFT-HANDED) M1 Loop Sign Table

OSEM Basis					EULER Basis				OSEM Basis				
Real Motion	OSEM Sensing	Elec. Gain	OSEMINF Gain	OSEM2EUL Gain	DAMP Gain	EUL2OSEM Gain	COILOUTF Gain	Elec. Gain	Current Sign	Magnet Polarity	OSEM Force	Real Motion	
+ L	- SD	+	+	-	-	-	-	+	-	S	Push	- L	
	+ F2	+	+	+	-	+	-	+	+	S	Pull		
+ T													- T
	+ F3	+	+	+	-	+	+	+	-	N	Pull		
	- LF	+	+	-	-	-	-	+	-	S	Push		
+ V													- V
	- RT	+	+	-	-	-	+	+	+	N	Push		
	- F1	+	+	-	-	-	+	+	+	N	Push		
+ R	+ F2	+	+	+	-	+	-	+	+	S	Pull	- R	
	+ F3	+	+	+	-	+	+	+	-	N	Pull		
	+ LF	+	+	+	-	+	-	+	+	S	Pull		
+ P													- P
	- RT	+	+	-	-	-	+	+	+	N	Push		
	+ F2	+	+	+	-	+	-	+	+	S	Pull		
+ Y													- Y
	- F3	+	+	-	-	-	+	+	+	N	Push		

Sensing Chain

Actuation Chain