



*LIGO Laboratory / LIGO Scientific Collaboration*

LIGO- E1200226-v3

Advanced LIGO

6/14/2012

**TwinCAT Library for Low Noise VCO**

Daniel Sigg

Distribution of this document:  
LIGO Scientific Collaboration

This is an internal working note  
of the LIGO Laboratory.

**California Institute of Technology**  
**LIGO Project – MS 18-34**  
**1200 E. California Blvd.**  
**Pasadena, CA 91125**  
Phone (626) 395-2129  
Fax (626) 304-9834  
E-mail: [info@ligo.caltech.edu](mailto:info@ligo.caltech.edu)

**Massachusetts Institute of Technology**  
**LIGO Project – NW22-295**  
**185 Albany St**  
**Cambridge, MA 02139**  
Phone (617) 253-4824  
Fax (617) 253-7014  
E-mail: [info@ligo.mit.edu](mailto:info@ligo.mit.edu)

**LIGO Hanford Observatory**  
**P.O. Box 159**  
**Richland WA 99352**  
Phone 509-372-8106  
Fax 509-372-8137

**LIGO Livingston Observatory**  
**P.O. Box 940**  
**Livingston, LA 70754**  
Phone 225-686-3100  
Fax 225-686-7189

<http://www.ligo.caltech.edu/>

<b>Library</b>	
Title	LowNoiseVco
Version	3
TwinCAT version	2.11
Name space	–
Author	Daniel Sigg
Description	<p>Controls the low noise VCO, <a href="#">D0900605</a></p> <p>The low noise VCO is based on a frequency difference divider. It requires a 71MHz/10dBm reference source and a VCO source at either 125MHz or 79MHz. Both RF levels as well as the RF level at the output of the frequency difference divider are monitored. The only set value is an offset into the VCO which translates into a frequency offset at the output. A binary output is used to enable the excitation input. Additional monitors are available for the tune voltage, the state of the excitation switch, and a power ok bit.</p> <p>If a frequency counter has been setup through the timing system, the measured frequency can be stabilized by feeding back to the bias offset. This then allows the user to select a fixed output frequency.</p> <p>The 3 RF power monitors which have the calibration</p> $P=12 \text{ dBm}-10 \text{ dBm/V} \times (U-4 \text{ V})$ <p>The corresponding temperature readout has the calibration</p> $T=20^{\circ}\text{C}+50^{\circ}\text{C/V} \times (U-6 \text{ V})$ <p>The RF power levels should be alarmed when outside <math>\pm 1\text{dBm}</math> of nominal.</p>
Error codes	<p>0x01 – Power supply voltages out-of-range</p> <p>0x02 – Reference RF power level out-of-range</p> <p>0x04 – Divider RF power level out-of-range</p> <p>0x08 – Output RF power level out-of-range</p> <p>0x10 – Frequency out-of-range</p> <p>0x20 – Invalid set frequency</p>
Library dependencies:	Error, ReadADC. WriteDAC

<b>Hardware Input Type</b> TYPE LowNoiseVcoInStruct : STRUCT ReferenceMon:                  INT; DividerMon:                  INT; OutputMon:                  INT; ReferenceTemp:              INT; DividerTemp:                INT; OutputTemp:                INT; TuneMon:                  INT; Frequency:                  LREAL; ExcitationSwitch:          BOOL; PowerOk:                  BOOL; FrequencyLive:              BOOL; END_STRUCT END_TYPE	
Type name	LowNoiseVcoInStruct
Description	Structure of the hardware inputs that are wired up for the low noise VCO
Definition	STRUCT
Element	Name: ReferenceMon Type: INT Description: Monitors the RF power at the reference input
Element	Name: DividerMon Type: INT Description: Monitors the RF power at the divider input
Element	Name: OutputMon Type: INT Description: Monitors the RF power after the output amplifier
Element	Name: ReferenceTemp Type: INT Description: Monitors the temperature of the reference RF detector
Element	Name: DividerTemp Type: INT Description: Monitors the temperature of the divider RF detector
Element	Name: OutputTemp Type: INT Description: Monitors the temperature of the output RF detector
Element	Name: TuneMon Type: INT

	Description: Monitor for the frequency offset
Element	Name: Frequency Type: LREAL Description: Measured frequency
Element	Name: ExcitationSwitch Type: BOOL Description: Monitors the excitation input enable
Element	Name: PowerOk Type: BOOL Description: Voltage monitor readback
Element	Name: FrequencyLive Type: BOOL Description: Keep alive for frequency measurement

<b>Hardware Output Type</b> TYPE LowNoiseVcoOutStruct : STRUCT TuneOfs:                    INT; ExcitationEn:              BOOL; END_STRUCT END_TYPE	
Type name	LowNoiseVcoOutStruct
Description	Structure of the hardware outputs that are wired up for the low noise VCO
Definition	STRUCT
Element	Name: TuneOfs Type: INT Description: Setpoint for the frequency offset
Element	Name: ExcitationEn Type: BOOL Description: Enables the excitation input

<b>User Interface Type</b>	
TYPE LowNoiseVcoStruct :	
STRUCT	
<pre> Error:                ErrorStruct; ReferenceMon:         LREAL; ReferenceNom:         LREAL; DividerMon:          LREAL; DividerNom:          LREAL; OutputMon:           LREAL; OuptutNom:           LREAL; ReferenceTemp:        LREAL; DividerTemp:         LREAL; OutputTemp:          LREAL; TuneOfs:             LREAL; TuneMon:             LREAL; ExcitationEn:        BOOL; ExcitationSwitch:    BOOL; PowerOk:             BOOL; Frequency:           LREAL; FrequencyLive:       BOOL; FrequencySet:        LREAL; FrequencyTol:        LREAL; FrequencyServoEn:    BOOL; FrequencyServoFault: BOOL; </pre>	
END_STRUCT	
END_TYPE	
Type name	LowNoiseVcoStruct
Description	Structure of the user interface tags that are used to control the low noise VCO
Definition	STRUCT
Output Tag	Name: Error Type: ErrorStruct Description: For error handler
Output Tag	Name: ReferenceMon Type: LREAL Description: Monitors the RF power at the reference input in dBm
Input Tag	Name: ReferenceNom Type: LREAL Description: Nominal value for the RF power at the reference input in dBm

Output Tag	Name: DividerMon Type: LREAL Description: Monitors the RF power at the divider input in dBm
Input Tag	Name: DividerNom Type: LREAL Description: Nominal value for the RF power at the divider input in dBm
Output Tag	Name: OutputMon Type: LREAL Description: Monitors the RF power after the output amplifier dBm
Input Tag	Name: OutputNom Type: LREAL Description: Nominal value for the RF power at the output amplifier in dBm
Output Tag	Name: ReferenceTemp Type: LREAL Description: Monitors the temperature of the reference RF detector in C
Output Tag	Name: DividerTemp Type: LREAL Description: Monitors the temperature of the divider RF detector in C
Output Tag	Name: OutputTemp Type: LREAL Description: Monitors the temperature of the output RF detector in C
Input Tag	Name: TuneOfs Type: LREAL Description: Setpoint for the frequency offset in V
Output Tag	Name: TuneMon Type: LREAL Description: Monitor for the frequency offset in V
Input Tag	Name: ExcitationEn Type: BOOL Description: Enables the excitation input
Output Tag	Name: ExcitationSwitch Type: BOOL Description: Monitors the excitation input enable
Output Tag	Name: PowerOk Type: BOOL Description: Voltage monitor readback
Output Tag	Name: Frequency Type: LREAL Description: Frequency of the VCO output
Output Tag	Name: FrequencyLive

	Type: BOOL Description: Indicates if the frequency of the VCO is updating
Input Tag	Name: FrequencySet Type: LREAL Description: Setpoint for the VCO frequency output
Input Tag	Name: FrequencyTol Type: LREAL Description: Tolerance for the VCO frequency output
Input Tag	Name: FrequencyServoEn Type: BOOL Description: Enables the frequency PID
Output Tag	Name: FrequencyServoFault Type: BOOL Description: Indicates a fault in the frequency servo



<b>Function Block</b> FUNCTION_BLOCK LowNoiseVcoFB VAR_INPUT LowNoiseVcoIn:       LowNoiseVcoInStruct; END_VAR VAR_OUTPUT LowNoiseVcoOut:     LowNoiseVcoOutStruct; END_VAR VAR_IN_OUT LowNoiseVco:        LowNoiseVcoStruct; END_VAR VAR END_VAR	
Name	LowNoiseVcoFB
Description	Controls the low noise VCO. One function block for each low noise VCO chassis needs to be instantiated.
Input argument	Name: LowNoiseVcoIn Type: LowNoiseVcoInStruct Description: Input hardware structure
Output argument	Name: LowNoiseVcoOut Type: LowNoiseVcoOutStruct Description: Output hardware structure
In/out argument	Name: LowNoiseVco Type: LowNoiseVcoStruct Description: User Interface structure

Visual	
Name	LowNoiseVcoVis
Description	Displays several MON and temperature readings, power and excitation status, and error alarms
Placeholder	Name: LowNoiseVCO Type: LowNoiseVCOstruct Description: Low Noise VCO structure